

Shipped in packet-tape reel(5,000pcs per reel)

Notice : It is requested to read and accept "IMPORTANT NOTICE" written on the back of the front cover of this catalogue.

#### Absolute Maximum Ratings

ltem	Symbol	Limit	Unit	
Max. Input Voltage	Vc	6	V	
Max.Input Current	I <sub>c</sub>	17	mA	
Operating Temp. Range	Topr.	−40 ~ +125	ĉ	
Storage Temp. Range	Tstg.	<i>−</i> 40 ~ +150	ĉ	

### ●Electrical Characteristics(Ta=25°C)

Item	Symbol	Conditions	Min.	Тур.	Max.	Unit
Output Hall Voltage	V <sub>H(i)</sub> <sup>#2</sup>	B=50mT, V <sub>C</sub> =3V	90		130	mV
Relative Output Voltage Ratio	V <sub>Hr</sub> <sup>**3</sup>	B=50mT, V <sub>C</sub> =3V	95		105	%
Input Resistance	R <sub>in</sub>	B=0mT, I <sub>C</sub> =0.1mA	370		570	Ω
Output Resistance	R <sub>out (i)</sub>	B=0mT, I <sub>C</sub> =0.1mA	750		1150	Ω
Relative Resistance Ratio	R <sub>outr</sub> **4	B=0mT, I <sub>C</sub> =0.1mA	95		105	%
Offset Voltage	V <sub>os</sub> (V <sub>u</sub> )	B=0mT, V <sub>C</sub> =3V	-6		+6	mV
Temp. Coefficient of V <sub>H</sub>	αV <sub>H</sub> <sup>**5</sup>	B=50mT, V <sub>C</sub> =3V Ta=25∼125℃		-0.2		%/°C
Temp. Coefficient of Rin	αRin <sup>™6</sup>	B=0mT, I <sub>C</sub> =0.1mA Ta=25∼125℃		-0.2		%/°C

%2.  $V_H = VHM - V_{os}(V_u)$  (VHM:meter indication)


\*3. VH(i)(i=1.2) is Hall output voltage of 2-Hall Elements of one package. VHr min=min(VH(i))/VHavg.X100, VHr max=max(VH(i))/VHavg.X100 Where VHavg.=(VH(1)+VH(2))/2

%4. Rout(i)(i=1.2) is output resistance of 2-Hall Elements of one package.  $Rout \ r \ min=min(Rout(i))/Rout \ avg. X100, \ Rout \ r \ max=max(Rout(i))/Rout \ avg. X100$ Routavg=(Rout(1)+Rout(2))/2


 $T_1 = 25^{\circ}C, T_2 = 125^{\circ}C$ 




#### Input Voltage Derating Curve



#### Input Current Derating Curve



Pinning




•Please be aware that our products are not intended for use in life support equipment, devices, or systems. Use of our products in such applications requires the advance written approval of our sales staff.

Certain applications using semiconductor devices may involve potential risks of personal injury, property damage, or loss of life. In order to minimize these risks, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards. Inclusion of our products in such applications is understood to be fully at the risk of the customer using our devices or systems.

•Handling precautions required for preventing electrostatic discharge.

•This product contains galium arsenide (GaAs).Handling and discarding precautions required.



i

### **IMPORTANT NOTICE**

- These products and their specifications are subject to change without notice. When you consider any use or application of these products, please make inquiries the sales office of Asahi Kasei EMD Corporation (AKEMD) or authorized distributors as to current status of the products.
- AKEMD assumes no liability for infringement of any patent, intellectual property, or other rights in the application or use of any information contained herein.
- Any export of these products, or devices or systems containing them, may require an
  export license or other official approval under the law and regulations of the country of
  export pertaining to customs and tariffs, currency exchange, or strategic materials.
- AKEMD products are neither intended nor authorized for use as critical components<sub>Note1</sub> in any safety, life support, or other hazard related device or system<sub>Note2</sub>, and AKEMD assumes no responsibility for such use, except for the use approved with the express written consent by AKEMD. As used here:

Note1) A critical component is one whose failure to function or perform may reasonably be expected to result, whether directly or indirectly, in the loss of the safety or effectiveness of the device or system containing it, and which must therefore meet very high standards of performance and reliability.

Note2) A hazard related device or system is one designed or intended for life support or maintenance of safety or for applications in medicine, aerospace, nuclear energy, or other fields, in which its failure to function or perform may reasonably be expected to result in loss of life or in significant injury or damage to person or property.

person or property.
 It is the responsibility of the buyer or distributor of AKEMD products, who distributes, disposes of, or otherwise places the product with a third party, to notify such third party in advance of the above content and conditions, and the buyer or distributor agrees to assume any and all responsibility and liability for and hold AKEMD harmless from any and all claims arising from the use of said product in the absence of such notification.

## ASAHI KASEI EMD CORPORATION

#### Headquaters

1-23-7 Nishi-Shinjyuku, Shinjyuku-ku, Tokyo 160-0023, Japan TEL: +81-3-6911-2800 FAX: +81-3-6911-2815

Osaka Office

1-2-6 Dojimahama Kita-ku,Osaka 530-8205,Japan

TEL. +81-6-6347-3133 FAX.+81-3-6911-2815

Europe Office

Market House, 19/21 Market Place, Wokingham, Berkshire, RG40 1AP, U.K.

TEL: +44-118-979-5777 FAX: +44-118-979-7885

#### Shanghai Office

Room2321,Shanghai Central Plaza,381 Huaihai Zhong Road,Shanghai 200020,Chaina TEL. +86-21-6391-6111 FAX.+86-21-6391-6686

Seoul Office

8th fi.,KTP B/D,27-2 Yoido-dong,Youngdungpo-gu,Seoul 150-742,Korea TEL. +82-2-3775-0990 FAX.+82-2-3775-1991

# AKM Semiconductor,Inc

Western US Sales

1731 Technology Dr Suito 500 San Jose,CA95110,USA TEL. +1-408-436-8580 FAX.+1-408-436-7591 Eastern US Sales 629 Bamford Road Cherry Hill,NJ 08003,USA TEL. +1-856-424-7211 FAX.+1-856-424-7344

#### URL

http://www.akemd.com

## North American Distributor: GMW Associates

 955 Industrial Rd, San Carlos, CA 94070, USA

 TEL. +1-650-802-8292
 FAX. +1-650-802-8298

 EMAIL sales@gmw.com
 WEB www.gmw.com